

ภาคผนวก B
รหัสแอสกีและเอ็บซีดีค (ASCII and EBCDIC)

Decimal	Binary	Octal	Hexa- decimal	ASCII	EBCDIC
0	00000000	0	C	NUL	NUL
1	00000001	1	D	.	.
2	00000010	2	E	,	,
3	00000011	3	F	;	;
4	00000100	4	10	'	'
5	00000101	5	11	"	"
6	00000110	6	12	#	#
7	00000111	7	13	\$	\$
8	00001000	10	14	%	%
9	00001001	11	15	&	&
10	00001010	12	16	'	'
11	00001011	13	17	((
12	00001100	14	18))
13	00001101	15	19	*	*
14	00001110	16	1A	+	+
15	00001111	17	1B	,	,
16	00010000	20	1C	-	-
17	00010001	21	1D	.	.
18	00010010	22	1E	/	/
19	00010011	23	1F		
20	00010100	24	20	space	
21	00010101	25	21	!	
22	00010110	26	22	"	
23	00010111	27	23	#	
24	00011000	28	24	\$	
25	00011001	29	25	%	
26	00011010	30	26	&	
27	00011011	31	27	'	
28	00011100	32	28	(
29	00011101	33	29)	
30	00011110	34	2A	*	
31	00011111	35	2B	+	
32	00100000	40	2C	,	
33	00100001	41	2D	-	
34	00100010	42	2E	.	
35	00100011	43	2F	/	
36	00100100	44	30	0	
37	00100101	45	31	1	
38	00100110	46	32	2	
39	00100111	47	33	3	
40	00101000	50	34	4	
41	00101001	51	35	5	
42	00101010	52	36	6	
43	00101011	53	37	7	
44	00101100	54	38	8	
45	00101101	55	39	9	
46	00101110	56	3A	A	
47	00101111	57	3B	B	

Decimal	Binary	octal	Hexa- decimal	ASCII	EBCDIC
48	00110000	60	30	0	
49	00110001	61	31	1	
50	00110010	62	32	2	
51	00110011	63	33	3	
52	00110100	64	34	4	
53	00110101	65	35	5	
54	00110110	66	36	6	
55	00110111	67	37	7	
56	00111000	70	38	8	
57	00111001	71	39	9	
58	00111010	72	3A	.	
59	00111011	73	3B	,	
60	00111100	74	3C	<	
61	00111101	75	3D	=	
62	00111110	76	3E	>	
63	00111111	77	3F	?	
64	01000000	100	40	@	blank
65	01000001	101	41	A	
66	01000010	102	42	B	
67	01000011	103	43	C	
68	01000100	104	44	D	
69	01000101	105	45	E	
70	01000110	106	46	F	
71	01000111	107	47	G	
72	01001000	110	48	H	
73	01001001	111	49		
74	01001010	112	4A	J	¢
75	01001011	113	4B	K	.
76	01001100	114	4C	L	<
77	01001101	115	4D	M	(
78	01001110	116	4E	N	+
79	01001111	117	4F	O	
80	01010000	120	50	P	&
81	01010001	121	51	Q	
82	01010010	122	52	R	
83	01010011	123	53	S	
84	01010100	124	54	T	
85	01010101	125	55	U	
86	01010110	126	56	V	
87	01010111	127	57	W	
88	01011000	130	58	X	
89	01011001	131	59	Y	
90	01011010	132	5A	Z	!
91	01011011	133	5B	[\$
92	01011100	134	5C	\	.
93	01011101	135	5D])
94	01011110	136	5E	^	↑
95	01011111	137	5F	_	←
96	01100000	140	60		□
97	01100001	141	61	a	/
98	01100010	142	62	b	
99	01100011	143	63	c	
100	01100100	144	64	d	
101	01100101	145	65	e	
102	01100110	146	66	f	

Decimal	Binary	octal	Hexa- decimal	ASCII	EBCDIC
103	01100111	147	67	g	
104	01101000	150	68	h	
105	01101001	151	69	i	
106	01101010	152	6A	j	
107	01101011	153	6B	k	
108	01101100	154	6C	l	%
109	01101101	155	6D	m	
110	01101110	156	6E	n	>
111	01101111	157	6F	o	?
112	01110000	160	70	p	
113	01110001	161	71	q	
114	01110010	162	72	r	
115	01110011	163	73	s	
116	01110100	164	74	t	
117	01110101	165	75	u	
118	01110110	166	76	v	
119	01110111	167	77	w	
120	01111000	170	78	x	
121	01111001	171	79	y	
122	01111010	172	7A	z	:
123	01111011	173	7B	{	#
124	01111100	174	7C		@
125	01111101	175	7D	}	'
126	01111110	176	7E		=
1 2 7	01111111	177	7F	DEL	"
128	10000000	200	80		
129	10000001	201	81		a
130	10000010	202	82		b
131	10000011	203	83		c
132	10000100	204	84		d
133	10000101	205	85		e
134	10000110	206	86		f
135	10000111	207	87		g
136	10001000	210	88		h
137	10001001	211	89		i
145	10010001	22i	91		j
146	10010010	222	92		k
147	10010011	223	93		l
148	10010100	224	94		m
149	10010101	225	95		n
150	10010110	226	96		O
151	10010111	227	97		p
152	10011000	230	98		q
153	10011001	231	99		r
162	10106010	24i	A2		s
163	10100011	243	A3		t
164	10100100	244	A4		u
165	10100101	245	A5		v
166	10100110	246	A6		w

Decimal	Binary	Octal	Hexa- decimal	ASCII	EBCDIC
167	10100111	247	A7		X
168	10101000	250	A8		Y
169	10101001	251	A9		Z
192	11000000	300	C0		}
193	11000001	301	C1		A
194	11000010	302	c2		B
195	11000011	303	c3		C
196	11000100	304	c4		D
197	11000101	305	C5		E
198	11000110	306	C6		F
199	11000111	307	C7		G
200	11001000	310	C8		H
201	11001001	311	C9		I
208	11010000	320	D0		}
209	11010001	321	D1		J
210	11010010	322	D2		K
211	11010011	323	D3		L
212	11010100	324	D4		M
213	11010101	325	D5		N
214	11010110	326	D6		O
215	11010111	327	D7		P
216	11011000	330	08		Q
217	11011001	331	D9		R
224	11100000	340	E0		\
225	11100001	341	E1		
226	11100010	342	E2		S
227	11100011	343	E3		T
228	11100100	344	E4		U
229	11100101	345	E5		V
230	11100110	346	E6		W
231	11100111	347	E7		X
232	11101000	350	E8		V
233	11101001	351	E9		Z
240	11110000	360	F0		0
241	11110001	361	F1		1
242	11110010	362	F2		2
243	11110011	363	F3		3
244	11110100	364	F4		4
245	11110101	365	F5		5
246	11110110	366	F6		6
247	11110111	367	F7		7
248	11111000	370	F8		8
249	11111001	371	F9		9
255	11111111	377	FF		

Note: Entries for which there is no character shown indicate that these codes have not been assigned or are used for control.